


## TEK FAZLI HARMONİK FİLTRELER



Ürün Modeli	Sipariş No	B. Fiyat / €	Güç (kVA)	L (mH)	I rms (A)	Ith (A)	Ilin (A)	C* (uF)	İşletme Gerilimi	Rezonans Frekans	P Faktörü	Koli Ağırlığı (kg)	Adet / Koli
ENT.ERH-E50 7-230-0,6	M5597	25,0	0,6	21,35	2,58	2,838	5,2	33,24	400V 50Hz	189 Hz	7%	0,95	1
ENT.ERH-E50 7-230-0,9	M5598	31,8	0,9	14,26	3,86	4,246	8,6	49,76	400V 50Hz	189 Hz	7%	1,4	1
ENT.ERH-E50 7-230-1,5	M5599	39,7	1,5	8,554	6,44	7,084	15,4	83	400V 50Hz	189 Hz	7%	2	1
ENT.ERH-E50 7-230-3	M5600	54,5	3	4,282	12,87	14,157	26,4	165,8	400V 50Hz	189 Hz	7%	2,9	1
ENT.ERH-E50 7-230-4,44	M5601	62,4	4,44	2,854	19,32	21,252	39,6	248,8	400V 50Hz	189 Hz	7%	3,7	1
ENT.ERH-E50 7-230-5,40	M5602	88,5	5,4	2,359	23,37	25,707	47,8	301	400V 50Hz	189 Hz	7%	3,95	1
ENT.ERH-E50 7-230-10,75	M5609	195	10,75	1,179	46,75	51,425	95,6	602	400V 50Hz	189 Hz	7%	6,5	1

## ÜÇ FAZLI HARMONİK FİLTRELER



Ürün Modeli	Sipariş No	B. Fiyat / €	Güç (kVA)	L (mH)	I rms (A)	Ith (A)	Ilin (A)	C* (uF)	İşletme Gerilimi	Rezonans Frekans	P Faktörü	Koli Ağırlığı (kg)	Adet / Koli
ENT.ERH-E50 7-400-0,83	M5543	79,5	0,83	46,14	1,36	1,50	2,43	5,44	400V 50Hz	189Hz	% 7	1,5	1
ENT.ERH-E50 7-400-1,25	M5542	108	1,25	30,64	2,04	2,24	3,65	8,19	400V 50Hz	189Hz	% 7	1,6	1
ENT.ERH-E50 7-400-1,5	M5541	124	1,5	25,53	2,45	2,70	4,38	9,83	400V 50Hz	189Hz	% 7	1,7	1
ENT.ERH-E50 7-400-2	M5581	128	2	18,13	3,04	3,50	5,52	16,38	400V 50Hz	189Hz	% 7	1,8	1
ENT.ERH-E50 7-400-4	M5251	141	4	9,58	9,54	7,19	11,69	26,20	400V 50Hz	189Hz	% 7	2,3	1
ENT.ERH-E50 7-400-5	M5250	148	5	7,66	8,17	8,99	14,61	32,75	400V 50Hz	189Hz	% 7	4,8	1
ENT.ERH-E50 7-400-6,25	M5249	148	6,25	6,13	10,21	11,23	18,26	39,03	400V 50Hz	189Hz	% 7	5	1
ENT.ERH-E50 7-400-8	M5247	159	8	5,11	12,26	13,49	21,92	47,16	400V 50Hz	189Hz	% 7	5,5	1
ENT.ERH-E50 7-400-10	M5246	174	10	3,83	16,34	17,97	29,22	65,50	400V 50Hz	189Hz	% 7	6,5	1
ENT.ERH-E50 7-400-12,5	M5245	194	12,5	3,07	20,42	22,46	36,51	78,60	400V 50Hz	189Hz	% 7	7	1
ENT.ERH-E50 7-400-15	M5244	229	15	2,56	24,55	27,02	52	92,51	400V 50Hz	189Hz	% 7	9,8	1
ENT.ERH-E50 7-400-16,6	M5243	247	16,6	2,3	25,33	27,83	53,20	102,3	400V 50Hz	189Hz	% 7	11,5	1
ENT.ERH-E50 7-400-20	M5242	257	20	1,92	30,5	33,55	49,10	130,99	400V 50Hz	189Hz	% 7	11,6	1
ENT.ERH-E50 7-400-22,2	M5241	276	22,2	1,73	33,85	37,24	54,50	145,40	400V 50Hz	189Hz	% 7	11,3	1
ENT.ERH-E50 7-400-25	M5240	277	25	1,53	38,12	41,93	61,37	163,74	400V 50Hz	189Hz	% 7	11,7	1
ENT.ERH-E50 7-400-30	M5239	292	30	1,28	45,23	50,31	88,23	185,02	400V 50Hz	189Hz	% 7	12,4	1
ENT.ERH-E50 7-400-35	M5238	314	35	1,09	53,37	58,70	85,92	229,23	400V 50Hz	189Hz	% 7	13,5	1
ENT.ERH-E50 7-400-40	M5237	329	40	0,95	60,99	67,09	98,20	261,98	400V 50Hz	189Hz	% 7	17,3	1
ENT.ERH-E50 7-400-44,4	M5236	354	44,4	0,86	67,7	74,47	109,00	273,81	400V 50Hz	189Hz	% 7	17,96	1
ENT.ERH-E50 7-400-50	M5235	366	50	0,77	76,24	83,86	102,75	314,38	400V 50Hz	189Hz	% 7	21,2	1
ENT.ERH-E50 7-400-60	M5234	452	60	0,645	85,94	94,534	137,504	366,96	400V 50Hz	189 Hz	% 7	26,5	1
ENT.ERH-E50 7-400-65	M5233	465	65	0,59	99,11	109,02	159,57	400,90	400V 50Hz	189Hz	% 7	27,75	1
ENT.ERH-E50 7-400-75	M5232	570	75	0,502	110,5	121,55	176,8	471,8	400V 50Hz	189Hz	% 7	30	1
ENT.ERH-E50 7-400-80	M5231	615	80	0,475	116,63	128,293	186,608	498,05	400V 50Hz	189Hz	% 7	34	1
ENT.ERH-E50 7-400-85	M5438	647	85	0,451	122,7	134,97	196,32	524,02	400V 50Hz	189Hz	% 7	26,5	1
ENT.ERH-E50 7-400-100	M5230	722	100	0,388	152,48	167,73	245,49	628,76	400V 50Hz	189Hz	% 7	42,5	1

50Hz dışında bir frekans ve p faktörü %5,67 veya %14 olan farklı güç değerlerindeki harmonik filtre ürünleri için fiyat sorunuz.